

AUTO STARTER BOX



MSB-F Standard Features:

- NEMA 4X enclosure
 - Push button ON & OFF
 - Reset push button
 - Back panel, terminal strip
 - IEC starter and adjustable overload
 - UL Listed
 - Enclosure sizes: 12" x 10" x 6"
14" x 12" x 8" for 15HP and up to 30HP.
 - Overload will be pre-set at the factory to the pumps corresponding FLA rating.
- (2) normally open mechanical float switches & 120 V control circuit**

P/N	HP	VOLTS	PHASE	PUMP MODEL	AMP RANGE
MSB1G060-F	0.5	115	1	All 400's - 115 Volt	5 to 7
MSB1G130-F	1	115	1	All 750's - 115 Volt	12 to 14
MSB1U070-F	1	230	1	All 750's - 230 Volt	6 to 8
MSB1U140-F	2	230	1	All 1500's - 230 Volt	13 to 15
MSB3U030-F	1	230	3	All 08's - 230 Volt	2 to 4
MSB3T015-F	1	460	3	All 08's - 460 Volt	1 to 2
MSB3U060-F	2	230	3	All 15's - 230 Volt	5 to 7
MSB3T030-F	2	460	3	All 15's - 460 Volt	2 to 4
MSB3U090-F	3	230	3	All 22's - 230 Volt	8 to 9.5
MSB3T045-F	3	460	3	All 22's - 460 Volt	3.5 to 5
MSB3U135-F	5	230	3	All 37's - 230 Volt	12 to 18
MSB3T068-F	5	460	3	All 37's - 460 Volt	5.5 to 8
MSB3U195-F	7.5	230	3	All 55's - 230 Volt	17 to 25
MSB3T095-F	7.5	460	3	All 55's - 460 Volt	7 to 10
MSB3U260-F	10	230	3	All 75's -230 Volt	23 to 32
MSB3T130-F	10	460	3	All 75's - 460 Volt	12 to 18
MSB3T175-F	15	460	3	KZN (H) 110-460T	12 to 18
MSB3T260-F	20	460	3	KZN 150-460T	23 to 32
MSB3T400-F	30	460	3	KZN 220-460T	37 to 50

MSB numbering system: KZN 110, 3 phase, 460 volts, 17.5 amps = MSB3T175-F

Voltage code: G = 115, U = 230, T = 460

F =120V float control system

CONTACT BJM PUMPS FOR 208 / 575 BOXES